
Cell Phone Signal Booster 3G WCDMA - 100Sqm

Main Features:

- Working System: 3G
 - Frequency Range: Uplink 1920-1980MHz; Downlink 2110-2170MHz
 - Coverage Area: 100Sqm
-

Technic Specifications:

- Working System: 3G
- Frequency Range: Uplink 1920-1980MHz; Downlink 2110-2170MHz
- Coverage Area: 100Sqm
- Power supply: AC/110-220V \pm 10% 45 \pm 55Hz
- Gain?Up link: Gp \geq 68dB, Downlink: Gp \geq 70dB
- Output up: Up link ?23dBm, Down link ?25dBm
- Port VSWR: \leq 1.8DB
- I/O impedance: 50 Ω /N connector
- ALC: \geq 10dB
- In-Band ripple: \leq 6dB
- Noise figure: \leq 6dB
- Transmission delay: \leq 0.5 μ s
- Weight: 1.07KG
- Dimension: 198*148*39mm

Images:





Package Included:

- 1pc Cell Phone Signal Booster 3G WCDMA - 100Sqm
- 1pc Power Adapter (100-240V)
- 1pc Indoor Antenna
- 1pc Outdoor Antenna
- Coaxial Cable 5M
- Coaxial Cable 10M
- Indoor Antenna Accessories and Screws
- Manual

Important Notice:

If you are not so sure about the Cell/Mobile Phone Frequency range you are going to booster, please kindly check your local cellular frequency at: <http://worldtimezone.net/gsm.html>

[product_url:] [Cell Phone Signal Booster 3G WCDMA - 100Sqm](#)

[pdf_url:] http://www.cellmobilephonejammer.com/CellPhoneSignalBooster3GWCDMA100Sqm435_22.pdf