

---

# Cell Phone Signal Booster Repeater 3G GSM - 80Sqm

---

## Main Features:

- Working System: 3G, GSM
- Frequency Range: Uplink GSM890-915MHz, 3G 1920-1980MHz; Downlink GSM935-960MHz, 3G2110-2170MHz
- Effective Coverage: 80 Square Metres

---

## Technic Specifications:

- Working System: 3G, GSM
- Frequency Range: Uplink GSM890-915MHz, 3G 1920-1980MHz; Downlink GSM935-960MHz, 3G2110-2170MHz
- Effective Coverage: 80 Square Metres
- Power supply: AC: 110-240V DC: 9V
- Gain: GSM: Up link:  $G_p \geq 70\text{dB}$ , Downlink:  $G_p \geq 75\text{dB}$ ; 3G: Up link:  $G_p \geq 70\text{dB}$ , Downlink:  $G_p \geq 75\text{dB}$
- Output up: GSM Up link  $25\text{dBm}$ , 3G Up link  $27\text{dBm}$ ; GSM Downlink:  $27\text{dBm}$ , 3G Downlink:  $27\text{dBm}$
- Port VSWR:  $\leq 1.8\text{dB}$
- I/O impedance:  $50\Omega$ /N connector
- ALC:  $\geq 20\text{dB}$
- In-Band ripple:  $\leq 6\text{dB}$
- Noise figure:  $\leq 6\text{dB}$
- Transmission delay:  $\leq 0.5\mu\text{s}$
- Ambient temperature:  $-15^\circ\text{C} \sim 55^\circ\text{C}$
- Size:  $220 \times 170 \times 55\text{mm}$

## Images:

---





## Package Included:

- 1pc Cell Phone Signal Booster Repeater 3G GSM - 80Sqm
- 1pc Power Adapter (100-240V)
- Indoor Antenna
- Outdoor Antenna
- Coaxial Cable 5M
- Coaxial Cable 10M
- Indoor Antenna Accessories and Screws
- User Manual

## Important Notice:

If you are not so sure about the Cell/Mobile Phone Frequency range you are going to booster, please kindly check your local cellular frequency at: <http://worldtimezone.net/gsm.html>

[product\_url:] [Cell Phone Signal Booster Repeater 3G GSM - 80Sqm](#)

[pdf\_url:] [http://www.cellmobilephonejammer.com/CellPhoneSignalBoosterRepeater3GGSM80Sqm433\\_22.pdf](http://www.cellmobilephonejammer.com/CellPhoneSignalBoosterRepeater3GGSM80Sqm433_22.pdf)