
Mobile Phone Signal Booster - Dual Band GSM900 DCS1800 1000Sqm

Main Features:

- Working System: GSM,DCS
- Frequency Range: Up link GSM 890-915/DCS1710-1785(MHz); Downlink GSM 925-960/DCS1805-1880(MHz)
- Effective Coverage: 1000 Square Metres

Images:





Technic Specifications:

- Working System: GSM,DCS
- Frequency Range: Up link GSM 890-915/DCS1710-1785(MHz); Downlink GSM 925-960/DCS1805-1880(MHz)
- Effective Coverage: 1000 Square Metres
- Power supply: AC110?220V±10% 45?55Hz
- Gain (dB): GSM/DCS Up link 65/53; GSM/DCS Downlink 70/58; Gain adjustable range MGC≥30dB
- Pass band ripple: GSM: 4 dB; DCS:15 dB
- I/O impedance: 50V/N Connector
- I/O return loss: ≤- 10 dB
- Noise figure: ≤- 8 dB
- Intermodulation attenuation(Po=13dBm): ≥40dBc
- Transmission Delay: ≤0.5us
- Guard band rejection: GSM (BW-60dB) ≤42 MHz?(BW-70dB) ≤ 45 MHz; DCS (BW-58dB) ≤104MHz ?(BW-60dB) ≤107MHz
- Dimension: 158 x 136 x 37 mm

Package Included:

- 1pc Mobile Phone Signal Booster - Dual Band GSM900 DCS1800 1000Sqm
- 1pc Power Adapter (100-240V)
- Indoor Antenna
- Outdoor Antenna

- Coaxial Cable 2M
- Coaxial Cable 10M
- Indoor Antenna Accessories and Screws

Important Notice:

If you are not so sure about the Cell/Mobile Phone Frequency range you are going to booster, please kindly check your local cellular frequency at: <http://worldtimezone.net/gsm.html>

[product_url:] [Mobile Phone Signal Booster - Dual Band GSM900 DCS1800 1000Sqm](#)

[pdf_url:]

http://www.cellmobilephonejammer.com/MobilePhoneSignalBoosterDualBandGSM900DCS18001000Sqm453_22.pdf