

---

## 5 Band Mobile Phone Jammer with Remote Control

---

### Main Features:

- Devices Blocked: Mobile Phone
- Signal Blocked: 3G,GSM,CDMA,DCS,PCS
- Effective Coverage: 40 Metres

### Images:

---





Wall installation indication

---

## Technic Specifications:

- Jamming frequencies:
  - CDMA 851-894MHz 35dBm 5dBm/30KHz(min)
  - GSM 925-960MHz 35dBm 5dBm/30KHz(min)
  - DCS 1805-1880MHz 33dBm -2dBm/30KHz(min)
  - PCS 1930-1990MHz 33dBm -2dBm/30KHz(min)
  - 3G 2110-2170MHZ 33dBm 0dBm/30KHz(min)
- Blocking Coverage: 40 Meters Depending on signal strength and working environment
- Total output power: 12Watt
- Energy Consumption: 30W
- Power supply: AC110-220V±10% / DC5V 45-55Hz
- Antenna: 5pcs Omnidirectional antennas
- Control: Wireless remote control (turn on and turn off)
- Working temperature: -40 ~ +55 degree centigrade
- Relative Humidity: 20%-95%
- Weight: 3KG
- Dimension: Antennas off - 210\*50\*210mm(L x W x D)

## Package Included:

- 1pc 5 Band Mobile Phone Jammer with Remote Control
- 1pc Power Adapter (110-240V)

- 1pc Manual

## **Important Notice:**

The item is for Legal Use only!

[product\_url:] [5 Band Mobile Phone Jammer with Remote Control \[CMPJ00016\]](#)

[pdf\_url:]

[http://www.cellmobilephonejammer.com/5BandMobilePhoneJammerwithRemoteControlCMPJ00016137\\_3.pdf](http://www.cellmobilephonejammer.com/5BandMobilePhoneJammerwithRemoteControlCMPJ00016137_3.pdf)