

---

## Cell Phone Signal Booster Repeater - GSM 850MHz/1900MHz 800Sqm

---

### Main Features:

- Working System: GSM
- Frequency Range: Up link GSM 824-849/PCS1850-1910(MHz); Downlink GSM 869-894/PCS1930-1990(MHz)
- Effective Coverage: 800 Square Metres

### Images:

---





---

## Technic Specifications:

- Working System: GSM
- Frequency Range: Up link GSM 824-849/PCS1850-1910(MHz); Downlink GSM 869-894/PCS1930-1990(MHz)
- Effective Coverage: 800 Square Metres
- Power supply: AC110?220V 45?55Hz
- Gain (dB): GSM/PCS Up link 50/45; GSM/PCS Downlink 50/45
- Pass Band Ripple: GSM 10dB; PCS: 15dB
- Guard Band Rejection: GSM (BW-60dB)  $\leq 42$  MHz (BW-70dB)  $\leq 42$  MHz; PCS (BW-60dB)  $\leq 104$  MHz (BW-70dB)  $\leq 104$  MHz
- I/O Return Loss  $\leq -10$ dB
- Noise Figure:  $\leq -8$ dB
- Intermodulation Attenuation (PO = 13dBm)  $\geq 40$ dBc
- Transmission Delay:  $\leq 0.5$  us
- Ambient Temperature: -10 degree – 50 degree C
- Dimensions: Signal Booster: 160 x 121 x 22 mm

## Package Included:

- 1pc Cell Phone Signal Booster Repeater - GSM 850MHz/1900MHz 800SqM
- 1pc Power Adapter (100-240V)
- 1pc Car Charger

- 1pc Manual

## **Important Notice:**

If you are not so sure about the Cell/Mobile Phone Frequency range you are going to booster, please kindly check your local cellular frequency at: <http://worldtimezone.net/gsm.html>

[product\_url:] [Cell Phone Signal Booster Repeater - GSM 850MHz/1900MHz 800Sqm](#)

[pdf\_url:]

[http://www.cellmobilephonejammer.com/CellPhoneSignalBoosterRepeaterGSM850MHz1900MHz800Sqm455\\_22.pdf](http://www.cellmobilephonejammer.com/CellPhoneSignalBoosterRepeaterGSM850MHz1900MHz800Sqm455_22.pdf)