
CellPhone Signal Repeater - CDMA800 PCS1900 1000 Square Meters

Main Features:

- Working System: CDMA800,PCS1900
- Frequency Range: Up link CDMA 824-849/PCS1850-1910(MHz); Downlink CDMA 869-894/PCS1930-1990(MHz)
- Effective Coverage: 1000 Square Metres

Images:





Technic Specifications:

- Working System: CDMA800,PCS1900
- Frequency Range: Up link CDMA 824-849/PCS1850-1910(MHz); Downlink CDMA 869-894/PCS1930-1990(MHz)
- Effective Coverage: 1000 Square Metres
- Power supply: AC110?220V±10% 45?55Hz
- Gain (dB): CDMA/PCS Up link 65/53; CDMA/PCS Downlink 70/58;Gain adjustable range? MGC≥30dB
- I/O impedance:50V/N Connector
- I/O return loss: ≤- 10 dB
- Noise figure: ≤- 8 dB
- Intermodulation attenuation(Po=13dBm): ≥40dBc
- Transmission Delay: ≤0.5us
- Guard band rejection : CDMA (BW-60dB) ≤42 MHz?(BW-70dB) ≤ 45 MHz; PCS (BW-58dB) ≤104MHz ?(BW-60dB) ≤107MHz
- Dimension: Signal Booster: 158 x 136 x 37 mm (L x W x D)

Package Included:

- 1pc CellPhone Signal Repeater - CDMA800 PCS1900 1000 Square Meters
- 1pc Power Adapter (100-240V)
- Indoor Antenna
- Outdoor Antenna
- Coaxial Cable 2M

- Coaxial Cable 10M
- Indoor Antenna Accessories and Screws
- Manual

Important Notice:

If you are not so sure about the Cell/Mobile Phone Frequency range you are going to booster, please kindly check your local cellular frequency at: <http://worldtimezone.net/gsm.html>

[product_url:] [CellPhone Signal Repeater - CDMA800 PCS1900 1000 Square Meters](#)

[pdf_url:]
http://www.cellmobilephonejammer.com/CellPhoneSignalRepeaterCDMA800PCS19001000SquareMeters447_22.pdf